

Installation Guide

Pocket Travel Router

Model: BL-MP01
VER: V3.0


Package list:



Wireless Access Point

Working on AP mode, BL-MP01 is a wireless transmitter which transfer wired signal into WiFi, so that other WiFi device can share wired signal, such as laptop or mobile phone.


Widely Used in: hotel, school dormitory, etc



Note:
Here it's Plug and Play. If unconnected to the Internet, please contact the network administrator.

Wireless Router

Working on RT mode, BL-MP01 is a wireless router which connect ADSL Modem to dial Internet, so that other WiFi device can share the signal from ADSL modem, such as laptop or mobile phone.
Widely Used in: family, apartment, etc



Steps:

A Turn BL-MP01 to **RT mode**, connecting device according to the above diagram.

B When already set wireless connection, please select "Obtain the IP and DNS automatically"

If have any questions, please refer to appendix One: IP Setting

C Wireless connection to the BL-MP01, the default SSID: BL-MP01-XXXXXX, X means the last six MAC address.

If have any questions, please refer to appendix Two: Wireless network connection


D Open the IE browser to log in the WEB management interface automatically (or input any website in the IE browser field), input User Name and Password to apply. Also you can change the SSID and the Password, refer to the following:

1. Select the third (PPPoE) mode
2. Input the User Name provided by ISP
3. Input the Password provided by ISP
4. Verify the Password again
5. Change SSID you like, such as John
6. Change the wireless key the length is more than eight characters
7. Click "Apply" to take effect

WiFi Repeater

Working on Repeater mode, BL-MP01 is a WLAN card. Easily amplify, relay and extend the range of weak signal by connect to other device.

Widely Used in: multiple buildings, big rooms, etc



Steps:

A Turn BL-MP01 to **Repeater mode**, connecting device according to the above diagram.

B When already set wireless connection, please select "Obtain the IP and DNS automatically"

If have any questions, please refer to appendix One: IP Setting

C Wireless connection to the BL-MP01, the default SSID: BL-MP01-XXXXXX, X means the last six MAC address.

If have any questions, please refer to appendix Two: Wireless network connection

D Open the IE browser to log in the WEB management interface automatically (or input any website in the IE browser field), refer to the following:

1. Choose the SSID you need, if not in the list, please click "Reset"
2. Click "connect" if the router has encryption, please input the previous setting key, the equipment will take effect after restarting automatically
3. When there shows an icon connected, it means access to wireless network successfully